

A FORCE TO BE RECKONED WITH.

EF3000iSE

3 kW Silent Inverter Electric Start Generator

The Powerful Portable Workhorse

Introducing the portable EF3000iSE Silent Inverter Electric Start Generator, delivering maximum output with minimum effort. This generator is powerful and portable with wheels for easy manoeuvrability.

What can it run?

- Fridge
- Desktop Computer
- Toaster
- Lights
- Hair Dryer
- Coffee Maker
- Belt Sander
- High Pressure Washer
- Air Compressor
- Kettle
- Television
- Portable Heater
- Laptop Computer
- Airconditioner
- Electric Hand Drill
- Chainsaw
- Bench Grinder
- Circular Saw

and much much more

This generator has all the power you will need and is a perfect for house and/or solar back up.

OPTIONAL REMOTE START

FEATURES AT A GLANCE

- **The Lightest Generator** in its class weighing only 67kg
- **USFS - Approved Spark Arrestor** eliminates errant sparks.
- **OHV Engine With Cast Iron Cylinder Liner** for longer life, powerful performance and excellent heat dissipation.
- **Smart Throttle™** varies engine speed based on load to improve fuel economy and reduce noise.
- **Inverter System with PWM** (Pulse Width Modulation) to safely run products with built-in microcomputers or microcomputer equipment / tools.
- **Petrol Petcock** helps prevent carburettor contamination during storage.
- **Oil Warning System** prevents engine damage.
- **Fuel Gauge** displays fuel levels without having to open the fuel cap.
- **Auto-Decompression System** reduces compression for effortless starting.



EF3000iS

4 YEAR WARRANTY

SPECIFICATION

| | EF3000iS |
|------------------------------|-----------------|
| Maximum Output | 3000 Watts |
| Rated Output | 2800 Watts |
| Operating Hours (1/4 Load) | 20.5 hr |
| Fuel Tank Capacity | 13 L |
| Size (LxWxH) | 680x445x555mm |
| Dry Weight | 67 kg |
| Noise Level (1/4 Load / 7m) | 51 dBA |
| Noise Level (Full Load / 7m) | 57 dBA |
| Starting System | Electric/recoil |
| Independent Fuel Tap | Yes |
| Fuel Gauge Monitor | Yes |
| Wheels | Yes |

- **Electrical Overload Breaker** prevents generator damage in case of overload.
- **Controls Located On One Panel** for easy access.
- **DC Outlet** with 8 Amp / 12 Volt outlet for charging batteries (cables included).
- **Rubber Isolation Feet** for smooth operation and noise absorption.
- **Easily Detachable Side Panels** for easier serviceability.
- **Noise Block™ Sound Reduction System** for performance so quiet, you'll forget the generator is even running.
- **Multi-Polar Alternator** for the generation of high quality, high frequency 3-phase AC current. This means a much lighter and a more compact unit when compared to conventional 2-pole rotor type alternators.

*All information and specs are subject to change without notice. Product running capabilities are dependant on the particular products wattage usage, not all appliances can run at the same time.

Yamaha data, September 2017.



1300 735 440

www.generator.yamaha.com.au